

Coaster pager W 11 CP

[w11ct]



Text pager coaster call device w11ct is our new style of coaster pager. Customer can be alert by sound and vibration, but also by text message. Not only simple sound or vibration alert. The approximate time or matter can be told from the pager, it is really advantage when customer hold the pager in the hospital, mall. They can manage their time quite well. If the customer do not hear the beeper sound or miss the vibration alert, you can also send a message just like a sms. You can advise your client "what, when, where" exactly. Very important, out of range alarm will alert the customer when he is out of the coverage of transmitter. It can work with pager transmitter W09Tr and W11Tk.

Key functions

1. PLL or crystal, 402-470Mhz, POCSAG
2. Alert mode: Sound, vibrate, LED
3. Out of range, low battery alert.
4. OTA setting by recommend transmitter

Specifications

Frequency Range: 402-470 MHz
Cap Codes: 8
Receiver Type: Synthesized or Crystal
Baud Rate: 1200, 2400 bps
Paging Sensitivity: -108DB @ 1200 bps, -106DB @ 2400 bps
Channel Spacing: 25 KHz or 12.5KHz
Frequency Deviation: +/-4.5 KHz
Frequency Stability: +/- 10 PPM
Selectivity: > 55dB
Image Rejection: > 52dB
Spurious Rejection: > 55dB
Intermediation: > 50dB
Alert Tone Loudness: 75dB+ @ 12 inch
Weight: 110 g with battery
Dimensions: 105mm (diameter) x16 mm (high)
Battery Type: Single AAA
Operating Temperature: -100 to 500 C

Compatible Equipment

- Transmitter W11tk
- Transmitter&Signal booster W09TR