

## Coaster pager W 11 CT

[w11ct]



Text pager coaster call device w11ct is our new style of coaster pager. Customer can be alert by sound and vibration, but also by text message . Not only simple sound or vibration alert. The approximate time or matter can be told from the pager, it is really advantage when customer hold the pager in the hospital, mall. They can manage their time quite well. If the customer do not hear the beeper sound or miss the vibration alert, you can also send a message just like a sms. You can advise your client “what, when, where ” exactly. Very important, out of range alarm will alert the customer when he is out of the coverage of transmitter. It can work with pager transmitter W09Tr and W11Tk.

### Key functions

1. PLL or crystal, 402-470Mhz, POCSAG
2. Alert mode: Sound, vibrate, LED
3. Out of range, low battery alert.
4. OTA setting by recommend transmitter

### Specifications

Frequency Range: 402-470 MHz  
Cap Codes: 8  
Receiver Type: Synthesized or Crystal  
Baud Rate: 1200, 2400 bps  
Paging Sensitivity: -108DB @ 1200 bps, -106DB @ 2400 bps  
Channel Spacing: 25 KHz or 12.5KHz  
Frequency Deviation: +/-4.5 KHz  
Frequency Stability: +/- 10 PPM  
Selectivity: > 55dB  
Image Rejection: > 52dB  
Spurious Rejection: > 55dB  
Intermediation: > 50dB  
Alert Tone Loudness: 75dB+ @ 12 inch  
Weight: 110 g with battery  
Dimensions: 105mm (diameter) x16 mm (high)  
Battery Type: Single AAA  
Operating Temperature: -100 to 500 C

### Compatible Equipment

- Transmitter W11tk
- Transmitter&Signal booster W09TR